

Thank you for purchasing a Shakespeare antenna product. Customer comments are welcome. Before installing, please study the diagram and check parts supplied against those listed.

IMPORTANT! Please read all instructions before installing.

The Style 5205 is a continuous-load, end-fed 1/2-wave CB Marine antenna with matching cable attached. This one-section 8' (2.4 m) antenna comes with a chrome-plated brass ferrule.

Tools required: Drill and 3/4" drill bit.

Installation Instructions

Choose a mounting location that is as high as possible, as free as possible from obstructions, and as far as possible from other antennas and strong sources of RF, but within reach of the antenna's cable. IMPORTANT: DO NOT CUT THE CABLE OR REMOVE THE CONNECTOR.

- Mount the antenna using a Shakespeare Style 4187 Ratchet Mount (sold separately) or use a Style 410-R Mounting Kit and a Style 4008 Extension Mast (each sold separately) to form a 16' (4.8 m) antenna system. Follow the instructions included with the mount you choose.
- 2. Route the cable to your transceiver, keeping it as far as possible from other electrical equipment and cables. Any excess cable should be rolled in a coil of at least 8" diameter and stowed in an out-of-the-way place, away from other electrical cabling.

DO NOT CUT OR ALTER THE CABLE, AND DO NOT REMOVE THE CONNECTOR. Drill a 3/4" hole for passage of the cable's connector, and use the (supplied) rubber grommet to seal the hole. The cable can be lengthened using suitable connectors and 50-ohm coax (each sold separately), either RG-58 or RG-8, without detrimental effect to antenna performance.

Cleaning Instructions

To clean the antenna, use mild dishwashing liquid (one that is not harsh to the hands and *without* ammonia) in lukewarm water.

WARNING: Do not let paint solvents, cleaning solvents, or adhesive caulking come in contact with the antenna. Chemicals in these materials might destroy the finish.

Supplied Parts 1 Antenna assembly 1 Rubber grommet **Antenna** Tech Tip This antenna will read "short circuit" when tested with an ohm meter or continuity tester. Cable to transceiver DO NOT CUT OR ALTER THIS CABLE Rubber grommet

Shakespeare Electronic Products Group

 $U.S.\ Operations:\ 6111\ Shakespeare\ Rd.\ \cdot\ Columbia,\ SC\ 29223\cdot 803-227-1590\cdot Fax:\ 803-419-3099\cdot www.shakespeare-marine.com$ $U.K.\ Operations:\ Enterprise\ Way,\ Fleetwood,\ Lancashire,\ FY7\ 8RY,\ England\cdot +44\ (0)\ 1253\ 858787\cdot Fax:\ +44\ (0)\ 1253-859595\cdot www.vtronix-antennas.com$