

IMPORTANT! Please read all instructions before installing.

WARNING: Installation of this product near power lines is dangerous! Check for overhead wires before installing.

Thank you for purchasing a Shakespeare antenna product. Shakespeare works hard to build reliability and durability into all of its products for maximum customer satisfaction.

The 390 is a 23', two-section SSB whip antenna with conductors running full length. The antenna's design supports power up to 1 KW. Its chrome-plated brass ferrule has 1"-14 threads. Use a Shakespeare 410-R Mounting Kit (sold separately).

TOOLS REQUIRED:

- Crescent wrench or 1/2" opened wrench

INSTALLATION INSTRUCTIONS

Choose a mounting location that is as high as practical, as free as possible from obstructions.

1. Thread the tip section onto the base section's upper ferrule, including the lockwasher as shown in the diagram, and securely tighten
2. Use 409 or 410 mounting hardware (not supplied) to mount the antenna to a deck or bulk-head. Instructions for installing the mounts are included with the mounting kits.
3. SSB antennas and radio require adequate grounding systems. Follow the radio manufacturer's instructions for connecting this antenna to your SSB radio.

WARNING

Installation of this product near power lines is dangerous! Check for overhead wires before installing!

TECH TIP: This antenna will read "shorted" from Point A to Point B (see diagram) when tested with an ohm meter or continuity tester.

SUPPLIED PARTS:

- 1 Base section antenna assembly
- 1 Tip section antenna assembly
- 1 3/8" Lockwasher

