

IMPORTANT! Please read all instructions before installing.

Thank you for purchasing a Shakespeare antenna product. Shakespeare works hard to build reliability and durability into all of its products for maximum customer satisfaction.

The 5421-XT is a Galaxy® Series AM/FM entertainment band antenna of 4' overall length and heavy duty construction. The one-section antenna has a stainless steel ferrule and a 12' cable with Motorola type plug attached.

INSTALLATION INSTRUCTIONS

Choose a mounting location as high as feasible, as free as possible from obstructions, and as far as possible from other antennas. Mount the antenna using a Shakespeare 4187 or 5187 Stainless Steel Ratchet Mount (each sold separately). Follow the instructions included with the mount you choose.

DO NOT CUT THE CABLE OR REMOVE THE CONNECTOR.

Route the cable to your AM/FM receiver and plug the Motorola type plug into the antenna jack. Any excess cable should be rolled in a coil at least 8" diameter and stowed in an out-of-the-way place.

The cable can be lengthened with a Shakespeare 4352 AM/FM 10' extension cable kit (sold separately).

CLEANING INSTRUCTIONS

To clean the antenna, use mild dishwashing liquid (one that is not harsh to the hands and *without* ammonia) in lukewarm water.

WARNING: Do not let paint solvents, cleaning solvents or adhesive caulking come in contact with the antenna. Chemicals in these materials might destroy the finish.

SUPPLIED PARTS:

- 1 Antenna assembly
- 1 Grommet plus (see Tech Tip)

TECH TIP: This antenna will read "short circuit" when tested with an ohm meter or continuity tester.

For installations where the cable exits through the bottom center of the antenna's ferrule, replace the grommet at the exit hole in the ferrule with the supplied Grommet Plug.

